

GUJARAT TECHNOLOGICAL UNIVERSITY**BE- VIIth SEMESTER-EXAMINATION – MAY/JUNE- 2012****Subject code: 171704****Date: 28/05/2012****Subject Name: Digital Signals and Systems****Time: 02:30 pm – 05:00 pm****Total Marks: 70****Instructions:**

1. Attempt all questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.

Q.1 (a) Determine the z-transform and sketch the ROC of **07**
 $x(n) = \{\sin \omega_0 n\}u(n)$

(b) Explain sampling theorem in detail. **07**

Q.2 (a) Describe the superiority of digital signal processing over **07**
 analog signal processing.

(b) Find the impulse response of the given system. **07**
 $y(n) = x(n) - 5/6y(n-1) + 1/6y(n-2)$

OR

(b) Determine the z-transform and sketch the ROC of **07**
 $x(n) = (1/3)^n, n > 0;$
 $= (0.5)^{-n}, n < 0;$

Q.3 For a given discrete time systems, check whether they are: **14**
 (1) Static or dynamic
 (2) Linear or non-linear
 (3) Shift invariant or shift-varying
 (4) Causal or non-causal
 (5) Stable or unstable
 Explain with reasons:
 (i) $e^{x(n)}$ (ii) $x(2n)$ (iii) $\text{Trunc}[x(n)]$

OR

Q.3 Obtain the linear convolution by graphical method of **14**
 following sequences.
 $x(n) = \{1, 4, 3, 2, 1\}$ and $h(n) = \{1, 2, 1, 2, 1\}$

Q.4 (a) Obtain Z-inverse of the following and comment on ROC. **07**
 $X(Z) = \frac{1 + Z^{-1}}{1 - Z^{-1} + 0.5Z^{-2}}$

(b) List out the symmetry properties of Fourier Transform for **07**
 discrete time signals.

OR

Q.4 (a) Explain comb filters with respective waveform. **07**
(b) Explain oversampling A/D Converters. **07**

Q.5 (a) Compute the DFT of the 4-point sequence **07**
 $x(n) = \{0, 1, 2, 3\}$
(b) Explain forward DCT with necessary equations. **07**

OR

Q.5 (a) Derive the frequency sampling structures of FIR filters. **07**
(b) Develop direct form II realization of IIR filter having **07**
 transfer function
 $H(Z) = \frac{1 + 0.8Z^{-1} - 2Z^{-2}}{6 - Z^{-1} + 0.55Z^{-2}}$
