

GUJARAT TECHNOLOGICAL UNIVERSITY**BE - SEMESTER-IV • EXAMINATION – WINTER • 2014****Subject Code: 142401****Date: 22-12-2014****Subject Name: Electro Mechanical Energy Conversion - I****Time: 02:30 pm - 05:00 pm****Total Marks: 70****Instructions:**

1. Attempt all questions.
2. Make suitable assumptions wherever necessary.
3. Figures to the right indicate full marks.

- Q.1** (a) State the principle of DC Generator. Enlist the various parts of the DC Machine and explain any three parts in detail. **07**
- (b) Explain the torque – speed characteristics of DC shunt motor. **07**
- Q.2** (a) Explain the working principle of 1-phase transformer. **07**
- (b) An 11000 / 230 V, 150-kVA, 1-phase, 50-Hz transformer has core loss of 1.4kW and full load copper loss of 1.6 kW. Determine: **07**
- (i) The kVA load for maximum efficiency and value of maximum efficiency at unity power factor.
- (ii) The efficiency at half of full load and 0.8 power factor leading.
- OR**
- (b) A 20-kVA, 440 / 220 V, 1-phase, 50-Hz transformer has iron loss of 324 W. The copper loss is found to be 110 W when delivering half full-load current. Determine: **07**
- (i) Efficiency when delivering full-load current at 0.8 lagging power factor.
- (ii) The percent of full-load when the efficiency will be maximum.
- Q.3** (a) Explain the construction and principle of operation of Induction Motor. **07**
- (b) A 3-phase induction motor is wound for 4-pole and is supplied from 50-Hz system. Calculate: **07**
- (i) The synchronous speed (ii) The rotor speed when slip is 3%.
- (iii) Rotor frequency when rotor runs at 500 rpm.
- OR**
- Q.3** (a) Explain the torque-slip and torque-speed characteristics of 3-phase induction motor and discuss the effect of rotor resistance on it. **07**
- (b) A 440-V, 3-phase, 50 Hz, 4 pole, Y connected induction motor has a full load speed of 1425 rpm. The rotor has an impedance of $(0.4 + j4) \Omega$ and rotor/stator turn ratio of 0.8. Calculate: **07**
- (i) Full load torque (ii) Rotor current (iii) full load rotor Cu loss
- Q.4** (a) Explain the construction of an alternator in detail. **07**
- (b) Explain the necessity of DC motor Starter and discuss on three point starter with neat sketch. **07**
- OR**
- Q.4** (a) Derive the equation for induced emf in an alternator. **07**
- (b) Explain the parallel operation of 3-phase alternator. **07**
- Q.5** (a) Explain – Schrage motor. **07**
- (b) Explain- linear induction motor. **07**
- OR**
- Q.5** (a) Write short note on: Stepper Motor. **07**
- (b) Explain the construction and torque speed characteristics of DC servo motor **07**
